

# Home Assignment

Problem 1: Consider the following dynamic system:

$$\frac{d}{dt} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix} = \begin{bmatrix} x_1^2 - x_2 + u \\ e^{x_2} - 3 \end{bmatrix}$$

If the steady state value of the input is  $u_s = 1$ , what are the steady state values of the states,  $x_{1s}$  and  $x_{2s}$ . Linearize the system around these steady state values.

Problem 2: Consider the following dynamic system:

$$\frac{d}{dt} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix} = \begin{bmatrix} x_1 x_2^2 - x_2 + u \\ x_1^3 - x_2^2 \end{bmatrix}$$

If the steady state value of the input is  $u_s = 0$ , what are the steady state values of the states,  $x_{1s}$  and  $x_{2s}$ . Linearize the system around these steady state values.